



# SHURE B帯ワイヤレスシステム / PSM300 (JB) 互換周波数リスト

BLX		PSM300	
1		1	
806.125	A-1	809.625	9-5

BLX		PSM300	
1		1	
806.250	b-1	809.625	9-5

BLX		PSM300	
1		1	
806.250	C-1	809.625	9-5

BLX		PSM300	
1		1	
806.375	d-1	809.625	9-5

BLX		PSM300	
1		1	
806.125	e-1	809.625	9-5

BLX		PSM300	
2		1	
806.125	A-1	809.625	9-5
806.875	A-2		

BLX		PSM300	
2		1	
806.250	b-1	809.625	9-5
807.000	b-2		

BLX		PSM300	
2		1	
806.250	C-1	809.625	9-5
807.000	C-2		

BLX		PSM300	
2		1	
806.375	d-1	809.625	9-5
807.250	d-2		

BLX		PSM300	
3		1	
806.125	A-1	809.625	9-5
806.875	A-2		
807.375	A-3		

BLX		PSM300	
3		1	
806.250	b-1	809.625	9-5
807.000	b-2		
807.500	b-3		

BLX		PSM300	
1		2	
806.125	A-1	809.625	9-5
		809.125	9-4

BLX		PSM300	
1		2	
806.250	b-1	809.625	9-5
		809.125	9-4

BLX		PSM300	
1		2	
806.375	d-1	809.625	9-5
		809.125	9-4

BLX		PSM300	
1		2	
806.125	A-1	809.500	2-6
		809.000	2-5

BLX		PSM300	
1		2	
806.250	b-1	809.500	2-6
		809.000	2-5

BLX		PSM300	
1		2	
806.375	d-1	809.500	2-6
		809.000	2-5

BLX		PSM300	
1		3	
806.250	b-1	809.625	9-5
		809.125	9-4
		808.125	9-3

BLX		PSM300	
1		3	
806.375	d-1	809.625	9-5
		809.125	9-4
		808.125	9-3

BLX		PSM300	
1		3	
806.125	A-1	809.500	8-5
		808.500	8-4
		808.000	8-3

BLX		PSM300	
2		2	
806.125	A-1	809.625	9-5
806.875	A-2	809.125	9-4

BLX		PSM300	
2		2	
806.250	b-1	809.625	9-5
807.000	b-2	809.125	9-4

BLX		PSM300	
2		2	
806.375	d-1	809.625	9-5
807.250	d-2	809.125	9-4

BLX		PSM300	
2		2	
806.125	A-1	809.500	2-6
806.875	A-2	809.000	2-5

PGX		PSM300	
1		1	
806.250	11	809.625	9-5

PGX		PSM300	
1		1	
806.375	21	809.625	9-5

PGX		PSM300	
1		1	
806.125	31	809.625	9-5

PGX		PSM300	
1		1	
806.250	61	809.625	9-5
807.250	62		

PG		PSM300	
1		1	
806.125	Ch1	809.625	9-5

PG		PSM300	
1		1	
806.375	Ch2	809.625	9-5

PG		PSM300	
1		1	
807.125	Ch3	809.625	9-5

SVX		PSM300	
1		1	
806.375	1	809.625	9-5

SVX		PSM300	
1		1	
807.625	2	809.625	9-5

SVX		PSM300	
1		1	
809.500	3	806.250	9-1

\*運用環境に依存するため、すべての互換周波数で運用を完全に保証するものではありません。